

## **DynaSample - XpressO** **update instructions**

File size update 2.0.0 rc4: „xpression\_update“ = 5.53 MB (5,806,080 Bytes) - Date: February-04-2019  
*Make sure to check correct filesize by right clicking on properties!*

=====  
Presets generated by older versions might not always be compatible with the latest update.  
It is recommended to copy all preset banks from the factory banks to the corresponding user banks.  
=====

### **Please notice:**

It takes several minutes - depending on the update size - until the update is completed. Do not switch off the device under any circumstances until the update is completed! The internal flash memory could get damaged and your XpressO might not start up anymore!

Do not connect any other USB device to the XpressO while updating the software!

- **Before starting the update make sure you have a USB drive ready that includes the unzipped update file!**
- **The USB drive has to be formatted with FAT32 (standard for pen drives)!**

### **Update execution:**

- 1) Unpack the file „**xpression\_update\_2.x.xx.zip**“ on a computer with any zip archive application.  
*This will unpack the files "xpression\_update" and „Update\_ReadMe.pdf“*
- 2) The file "**xpression\_update**" has to be copied to the top level (i.e. not inside of a folder) of a USB memory device such as a USB pen drive (or USB hard disk).
- 3) Turn the wheel on the left hand of the XpressO counterclockwise once until **Utility** appears, then **press briefly onto the right data wheel for [OK]**.
- 4) Turn the left wheel counterclockwise again until you see „**Software Update**“ and press **[OK]**.
- 5) When the display shows „**press OK to start update**“ press **[OK]**.
- 6) Now the device is restarting in update mode. Do not connect your USB drive, yet!
- 7) Upon request insert your USB drive into any USB port of the XpressO and when you see “Do Not Switch Off” press **[OK]**.
- 8) The unit will now search for the update file and copy the relevant data onto the internal flash memory of the XPression.  
This may take several minutes - do not turn off the device under any circumstances!
- 9) After the update has been completed the unit will shut down automatically.  
Remove the USB drive and restart. While starting up the new software version number will be displayed.

You can also check the current software version manually by going to the **Utility** menu.  
Then move to the left until **Serial Number** appears on the display. The bottom line shows the current software version.

Pressing briefly onto the left wheel **[Escape]** will (always) take you back to the main display page.

In case of the error message „**no valid update file found**“ please check the size of the file „**xpression\_update**“. If the size is incorrect download the update file once more and start over from the beginning.

Make sure that there is no other USB device connected to the XpressO during the update.

Please check for the latest update of the operating manual at [www.dynasample.com/xpresso](http://www.dynasample.com/xpresso)

In case of any problems please contact DynaSample by email: [support@dynasample.com](mailto:support@dynasample.com)

# DynaSample - XPression

## Update - Anleitung

Datei-Größe Update 2.0.0 rc4: „xpression\_update“ = 5,53 MB (5.806.080 Bytes) – Datum 04.02.2019  
*unbedingt mit Rechtsklick auf Eigenschaften überprüfen!*

=====  
Presets von vorherigen Versionen sind unter Umständen nicht kompatibel zur aktuellsten Version.  
Wir empfehlen die Presets von der Factory-Bank auf die User-Bänke zu kopieren.  
=====

### **BITTE UNBEDINGT BEACHTEN:**

Es kann je nach Updategröße einige Minuten dauern bis das Update abgeschlossen ist. Auf gar keinen Fall darf während des Updates das Gerät ausgeschaltet werden! Der Speicher kann irreparabel beschädigt werden und das Gerät könnte dann gegebenenfalls nicht mehr starten!

Es dürfen keine anderen USB-Geräte während des Updates an den XpressO angeschlossen sein!

- **Es muss ein USB-Stick mit der entpackten Datei "xpression\_update" bereit liegen!**
- **Der USB Stick muss mit FAT32 formatiert sein!**

### **Ausführung:**

- 1) Entpacken Sie die „**xpression\_update\_2.x.xx.zip**“ - Datei auf einem Computer mit einem ZIP-Archiv-Programm.  
*Darin sind die Dateien "**xpression\_update**" und „**Update\_ReadMe.pdf**“ enthalten.*
- 2) Die Datei "**xpression\_update**" muss auf die oberste Ebene (d.h. nicht in einem Ordner) eines USB-Laufwerks (z. B. eines USB-Sticks) kopiert werden.
- 3) Drehen Sie am XpressO das linke Datenrad einmal gegen den Uhrzeigersinn bis **Utility** erscheint und **drücken Sie kurz auf das rechte Datenrad für [OK]**.
- 4) Drehen Sie den linken Drehregler gegen den Uhrzeigersinn bis zu „**Software Update**“ und drücken Sie **[OK]**.
- 5) Es erscheint „**OK drücken um das Update zu starten**“. Drücken Sie nochmals **[OK]**.
- 6) Das Gerät macht nun einen Neustart im Update-Modus. Verbinden Sie den USB-Speicher noch nicht!
- 7) Auf Aufforderung verbinden Sie dann das USB-Laufwerk mit einem beliebigen USB-Port am XpressO und drücken **[OK]**.
- 8) Der XpressO sucht nun nach dem Update und kopiert die entsprechenden Dateien auf den internen Flash-Speicher.  
Dies kann einige Minuten dauern. Schalten Sie das Gerät dabei auf gar keinen Fall aus!
- 9) Wenn das Update beendet ist, fährt das Gerät automatisch herunter.  
Entfernen Sie den USB-Speicher und schalten Sie das Gerät erneut ein. Beim Start sollte die neue Versionsnummer auf dem Display angezeigt werden.

Sie können die aktuelle Software-Version auch manuell überprüfen, indem Sie das **Utility** - Menü aufrufen. Danach drehen Sie den linken Drehregler gegen den Uhrzeigersinn bis **Serien-Nummer** angezeigt wird. Darunter sehen Sie die aktuelle Software-Version.

Durch kurzes Drücken auf das linke Datenrad **[Escape]** kehren Sie (immer) zur Hauptseite zurück.

Sollte der Fehler „**no valid update file found**“ auftauchen, überprüfen Sie bitte die Größe der Datei „**xpression\_update**“ und laden Sie sie gegebenenfalls nochmals herunter. Beginnen Sie dann nochmals von vorne. Stellen Sie sicher, es ist kein anderes USB-Gerät am XPression angeschlossen.

Bitte laden Sie auch die neueste Version der Anleitung unter [www.dynasample.com/xpresso](http://www.dynasample.com/xpresso) herunter.

Bei Problemen kontaktieren Sie bitte DynaSample per Email: [support@dynasample.com](mailto:support@dynasample.com)

## VERSION HISTORY

### 2.0.00

- ToDo for final release version 2.0.0:
- display the currently stored audio file correctly when editing backing tracks in [**Play**]
- the karaoke sound file parameters (like volume, start note, etc.) are to be saved in a separate process
- program maps can currently only be entered manually in [**Global**]
- page jump is currently not working
- new samplevoice that plays legato without the need of overlapping two voices (= XpressO plays 2 voices)
- new Multi Preset to replace Keysplit, Chord-Mapper sound assign and external instruments
- unify the XpressO and XPression software

### 2.0.00 RC4

- RC4 (February-04-2019)
- an error that left the system drive in the write enabled state after updating has been fixed.  
**PLEASE RUN THE UPDATE TWICE** to insure that your system drive is properly write protected.
- optimized the responsiveness of the user interface (buttons & wheels)
- hot plugging of USB-MIDI is now possible (only one USB-MIDI device plus midiBeam is recognized)
- the EWI-USB SysEx setup is correctly transmitted now during startup or hot plugging (when enabled)

### 2.0.00 RC3

- RC3 (January-24-2019)
- the pitchbend range is editable now
- the mic input has been activated
- backing tracks / karaoke are working now
- reset does not cause double notes and overloads anymore
- eliminated strange delayed portamento when using pitchbend on the cello patch F1-64
- the left wheel for navigating through the menus does not make the unit unresponsive anymore

### 2.0.00 RC2

- RC2 (December-2018)
- initial release for the XpressO